

NOTE: To activate clock, pull plastic tab on back to connect batteries

CONTROL BUTTON DESCRIPTIONS:

- | | |
|--|---|
| <ul style="list-style-type: none"> 1) TALK: Speaks current time and date and confirms time setting 2) ALARM CHECK: Scrolls through alarm times and Confirms Alarms Settings 3) LIGHT: Turns on LCD backlight for 6 seconds 4) ALARM ACKNOWLEDGED: When the alarm is sounding, stops the alarm and tells when next alarm is due 5) LCD TIME DISPLAY: Digital display of the current time 6) LCD ALARM INDICATION: Shows which of the (6) available alarms are currently turned on and active 7) LCD DAY DISPLAY: Digital display of the day of the week 8) LCD DATE DISPLAY: Large digital display of the Date 9) ALARM OFF/ BEEP/ VOICE: Master Alarm Function settings including Off, Beeping only alarm, and Voice and Beeping alarm | <ul style="list-style-type: none"> 10) MODE SELECTION: Used to toggle between setting the clock, setting the alarm and locking the clock into "Run" Mode 11) SET/ ADVANCE: Advances through each step of the setting procedures 12) " - " : Setting Selection backward 13) " + " : Setting Selection forward 14) ALARM SELECTION: Sliding switch is used to select each of the individual alarms during all modes 15) MIC: Microphone input used for recording alarm messages 16) RECORD: When pressed and held, used to record selected alarm message 17) ERASE: When pressed and held, erases recording for selected alarm 18) PLAY: Plays the current recorded message for the selected alarm 19) POWER ADAPTER INPUT: Input for included AC Adapter
ANS: Input: 120V AC 60Hz, Output: 5V DC 450mA |
|--|---|

SETTING THE CURRENT TIME/ CALENDAR:

Setting sequence: Hour set> Minute Set> Month Set> Date Set> Year Set

Slide "**MODE SELECTION**" @ switch to "TIME SET".

Press "**SET/ ADVANCE**" ID button once to enter **Hour Set Mode**.

Use "- " @ and "+ a) buttons on the back to select the current hour.

Press "**SET/ ADVANCE**" ID once to enter **Minute Set Mode**, use "-" and "+" to select the current minute.

Press "**SET/ ADVANCE**" ID once to enter **Month Set Mode**, use "-" and "+" to select the correct month.


Press "**SET/ ADVANCE**" ID once to enter **Date Set Mode**, use "-" and "+" to select the correct date.

Press "**SET/ ADVANCE**" ID once to enter **Year Set Mode**, use "-" and "+" to select the correct year.

Press green "**TALK**" 0 button on top of the clock once to confirm the time settings and exit

Time Set Mode. The Your Minder Clock will now speak the current time and date.

Slide "**MODE SELECTION**" @ switch back to "LOCK/ RUN".



NOTE: If no buttons are pressed within 1 minute, the clock will exit TIME SET MODE automatically.

SETTING THE ALARM TIMES:

NOTE: The Alarms are preset to default to 7:00 AM, 9:00 AM, 12:00 PM, 3:00 PM, 6:00 PM and 9:00 PM when batteries are inserted into the MedCenter Clock.

Slide "**ALARM SELECTION**" m switch to the alarm [1 - 6] you wish to set.

Slide "**MODE SELECTION**" @ switch to "ALARM SET".

Press "**SET/ ADVANCE**" ID button to enter **Alarm Set Mode**.

Use "- " @ and "+ a) buttons to select the current hour:

Press "**SET/ ADVANCE**" ID once to enter **Alarm Minute Set Mode**, use "-" and "+" to select alarm minute.

Press "**SET/ ADVANCE**" ID once to enter **Alarm ON/OFF Set Mode**, use "-" and "+" to toggle alarm on/ off.


Press blue "**ALARM CHECK**" 8 button on top of the clock to confirm the alarm settings and exit **Alarm Set Mode**.

Repeat the above steps for each of the 6 alarm times you wish to set.

Slide "**MODE SELECTION**" @ switch back to "LOCK/ RUN".

To Turn Off all 6 Alarms, slide "ALARM OFF/ BEEP/ VOICE" 0 switch to "OFF" Position

NOTE: If no buttons are pressed within 1 minute, the clock will exit TIME SET MODE automatically.



RECORDING YOUR OWN ALARM MESSAGES

Note: Personal message Max Recording Time is 10 seconds per alarm. When no personal message is recorded for a selected alarm, a Beeping alarm will be used as default.

- Slide "ALARM SELECTION" switch to the alarm you wish to set.
- Press and hold "RECORD" button when you are ready to record your message. A 'Beep' will notify you that the recording has begun. Speak clearly into the "MIC" on the back of the Your Minder Clock. For the clearest recording, speak at a distance of 6" from the "MIC".
- Release "RECORD" button once you have completed your message. A 'Beep' will notify the end of the recording.
- Press "PLAY" to listen to your recorded message. If unsatisfied with playback, repeat above steps as necessary.

DELETING A RECORDED ALARM MESSAGE

- Slide "ALARM SELECTION" switch to the alarm you wish to delete. Press "PLAY" to confirm your selection.
- Press and hold "ERASE" button until you hear a 'Beep' to confirm the message has been deleted. Press "PLAY" button to confirm that the recorded message has been deleted. See "Recording Your Own Alarm Messages" above to record a new message for this alarm.



USING THE YOUR MINDER CLOCK:

DURING NORMAL DAILY OPERATION:

- For a reminder when the next active alarm is due, press the red "ALARM ACKNOWLEDGED" button.
- For an update of each alarm's status, press the blue "ALARM CHECK" button.
- For a check of the current time, press the green "TALK" button.
- To turn on the LCD Light, press the yellow Light button. The light remains on for 6 seconds.

WHILE ALARM IS SOUNDING:

- Press the red "ALARM ACKNOWLEDGED" button to stop the alarm. The clock will now confirm the alarm has been accepted and notify you when the next alarm will sound.



BATTERY AND AC ADAPTER INFORMATION

- We recommend using the included AA Batteries as a backup power source and using the included AC Adapter as the primary power source. In the event of a loss of power, the installed AA Batteries will support the clock running normally until power can be restored.
- In the event of a loss of power, you should not lose your recorded messages because the recorded messages are stored in internal memory.
- Under normal operation, with daily alarms sounding for 1 minute every day, the Your Minder clock can run up to 6 months on two AA Batteries.
- The AA Batteries also allow the Your Minder clock to operate as a Traveling Alarm Clock.

NOTE: Excessive operation of the backlight, allowing the recorded alarms to run their full hour duration, and frequent talking alarm or time checks will all affect the life expectancy of the installed AA Batteries.



PRODUCT DISCLAIMERS & WARNINGS: Please Read carefully

- Do not connect an A/C power adaptor other than the recommended unit as irreparable damage may result and void your warranty. Contact your supplier for power supply availability details.
- Only use good quality AA batteries with YourMinder and do not mix old and new batteries as leakage damage may result.
- When using YourMinder with the optional power supply avoid locating it close to a source of water or potential spillage.
- The YourMinder is a personal reminder and is not intended to replace human care interaction.
- Replace the AA batteries annually (if used with the A/C power adaptor) or when the low battery indicator is activated or when sound quality or alarm volume is noticeably reduced.

WARRANTY INFORMATION Please Read carefully

The YourMinder Clock and MedCenter System are guaranteed for one year from the date of purchase to be free of manufacturer defects.

The warranty is void if the Your Minder Clock is water damaged (it is not specified to be water resistant).

The warranty is void if the Your Minder Clock or MedCenter System is damaged, tampered with, dropped or otherwise abused.

In the event of a defect, contact your supplier (where you purchased the YourMinder) for further instructions.